


# FC-7564 WIRING DIAGRAM



## Power supply

- Only can use 12V/7A sealed lead-acid battery, change battery every 3-5 years
- With 1 keypad, power consumption 250mA, support for 16 working hrs.
- Total power consumption (keypad, auxiliary power, siren) can't exceed max. power consumption of control panel
- Max. Rechargeable current of battery: 350MA

# Foreword

FC-7564 is a intelligent alarm control system which in tegrated with burglarproof, fireproof, gas leak proof. It is compatible with wired and wireless alarm mode.

FC-7564 refers to the most advanced coding techniques of BUS zone and multi-bit random code-hopping techniques in security & reliability, to avoid false alarm and interference effectively.

- 1.64 zones:8 wired, 24 wireless and 32 BUS zone
- 2.6 way to arm and disarm the system: User code, Keyfob, Phone, SMS, Auto timer, CMS
- 3.Alarm notification: When alarm occurs, user can have alarm notification by phone call, SMS, GPRS, TCP/IP(optional)

## Smart feature of FC-7564

1. Multi-zones combination alarm, special design for the places suchas watchroom, bedromm and etc.
- 2.Can use without keypad
- 3.LED display on metal case, easier for user to check system info.

### Warning!!!

- Don' t disassemble or modify, or else may be lead to danger and the damage of panel.
- Be sure not to cause to break by falling or throwing down or strong impacting. Not install near the magnetic field, may because instability.
- Keep dry and clean. Don' t install the panel in the site which has oily fume, water-vapour, much poudre.
- Be keep out of the sun and heat. Don' t install the panel near the heating stove etc. high temperature equipment, such as spotlight. Keep out of the direct sunlight, may cause color fading.
- When cleaning, wipe with the mull. To remove dirt need to use detergent, don' t use gasoline or paint thinner etc. chemicals. Or else may cause damage or the paint scaled off the panel.

## Features:

Zones: 8 wired/24wireless/32BUS zone

Keypad and remote: Support 8pcs LCD keypad and 8remotes

Password: 1 installer code, 1 duress code, 15 user codes

CMS: 2 CMS follow me numbers, 1 account number

Voice number: 4 voice numbers, Voice prompting operation

Event log: 128 event logs

Module expanded: GSM/GPRS module

Recording: 10-second automatic message Recording

## Alarm procedure

